

# CR3AMZ

LOW POWER, STROBE USE  
NON-INSULATED TYPE, GLASS PASSIVATION TYPE


## CR3AMZ



- $I_T (AV)$  ..... 0.4A
- $V_{DRM}$  ..... 400V
- $I_{GT}$  ..... 30mA

## OUTLINE DRAWING

Dimensions  
in mm



TO-202

## APPLICATION

Automatic strobe flasher

## MAXIMUM RATINGS

Symbol	Parameter	Voltage class	Unit
		8	
$V_{RRM}$	Repetitive peak reverse voltage	400	V
$V_{RSM}$	Non-repetitive peak reverse voltage	480	V
$V_{DRM}$	Repetitive peak off-state voltage	400	V
$V_{DSM}$	Non-repetitive peak off-state voltage	480	V

Symbol	Parameter	Conditions	Ratings	Unit
$I_T (AV)$	Average on-state current	Commercial frequency, sine half wave, 180° conduction,	0.4	A
$I_{TRM}$	Repetitive peak on-state current *1	$C_M=700\mu F$ with discharge current	200	A
$P_{GM}$	Peak gate power dissipation		0.5	W
$P_G (AV)$	Average gate power dissipation		0.1	W
$V_{FGM}$	Peak gate forward voltage		6	V
$I_{FGM}$	Peak gate forward current		0.5	A
$T_j$	Junction temperature		-40 ~ +125	°C
$T_{stg}$	Storage temperature		-40 ~ +125	°C
—	Weight	Typical value	1.1	g

\*1. Refer to sections 1, 2 on STROBE FLASHER APPLICATION shown in the last sheet for CR3JM.

# CR3AMZ


LOW POWER, STROBE USE  
NON-INSULATED TYPE, GLASS PASSIVATION TYPE

## ELECTRICAL CHARACTERISTICS



Symbol	Parameter	Test conditions	Limits			Unit
			Min.	Typ.	Max.	
IRRM	Repetitive peak reverse current	$T_j=25^{\circ}\text{C}$ , $V_{RRM}$ applied	—	—	0.1	mA
IDRM	Repetitive peak off-state current	$T_j=25^{\circ}\text{C}$ , $V_{DRM}$ applied	—	—	0.1	mA
$V_{TM}$	On-state voltage	$T_a=25^{\circ}\text{C}$ , $I_{TM}=3\text{A}$ , Instantaneous value	—	—	2.0	V
$V_{GT}$	Gate trigger voltage	$T_j=25^{\circ}\text{C}$ , $V_D=6\text{V}$ , $R_L=6\Omega$	—	—	1.5	V
$V_{GD}$	Gate non-trigger voltage	$T_j=125^{\circ}\text{C}$ , $V_D=1/2V_{DRM}$	0.1	—	—	V
$I_{GT}$	Gate trigger current	$T_j=25^{\circ}\text{C}$ , $V_D=6\text{V}$ , $R_L=6\Omega$	—	—	30	mA
$C_c$	Commutating capacitor *2	$C_M=700\mu\text{F}$ , $V_{CM}=350\text{V}$ , $I_{TM}=200\text{A}$ , $L=25\mu\text{H}$ , $T_a=25^{\circ}\text{C}$	—	—	2.2	$\mu\text{F}$

\*2. Refer to section 3 on STROBE FLASHER APPLICATION shown in the last sheet for CR3JM.

Fig 1. TEST CIRCUIT FOR COMMUTATING CAPACITOR









## PERFORMANCE CURVES



# CR3AMZ

LOW POWER, STROBE USE  
NON-INSULATED TYPE, GLASS PASSIVATION TYPE



# CR3AMZ

LOW POWER, STROBE USE  
NON-INSULATED TYPE, GLASS PASSIVATION TYPE

